


- > 6200/6300/6500/6600/6700
- > DIN Power supplies
- > for operation using:
 - momentary switch
 - relay



1 x connector for 24V DC power plug

- > coaxiale power plug
- > 'center positive'
- > min. 22V
- > max. 28V
- > 2,1 x 5,5 x 10-11 mm

| DIN Power Supplies | P [W] | DIN Power Supplies | P [W] |
|--------------------|-------|--------------------|-------|
| 6030-DR-075 | 75W | 6030-DR-240 | 240W |
| 6030-DR-120 | 120W | 6030-DR-480 | 480W |

Connector for RJ45 plug (type B) connector 2 (black)

connect wires necessary only

| Rail type | P *) | max. cable length per diameter | | |
|------------------|------|--------------------------------|-------------------|---------------------|
| | | 0,75mm ² | 1 mm ² | 1,5 mm ² |
| 6200, 6500, 6700 | 45W | 23m | 30m | 45m |
| 6300, 6600 | 20W | 56m | 75m | 112m |

*) medium weight curtain, 'room' height, glider 4010, no heading

| Switching | |
|-----------|---|
| 0 | <i>Open</i> and <i>close</i> should not be activated simultaneously. If so, the motorunit will switch to the programming mode |
| 0 | Pulse < 1,2 sec: - automatic complete open/close - stop |
| 0 | Pulse > 1,2 sec: the system runs untill button is released or untill the end position is reached |
| 0 | Connect every motor unit individually to the DIN power supply |
| 0 | Bounce time lower than 0,04 sec required |
| 0 | The switching current is +/- 5,5mA |
| 0 | 24V out pin2 and pin4: max. 2,4VA 5V out pin3 and pin4 |
| 0 | Potential free switching only |

